



MC-1500

19-inch Media Converter Chassis

Providing more capacity to the converters in one chassis, the MC-1500 provides 15-slot in the 19"-rack saving more spaces for fiber-optic wiring yet ease the maintenance of media conversion.

The MC-1500, media chassis allows connectivity of up to fifteen PLANET Ethernet/ Fast Ethernet Gigabit Ethernet Converter in one chassis. Two fans with LED indicators for system cooling keep you informed the system and FAN status.

Independent power supply in each bay of the MC-1500, you can freely install the converters without interrupting the rest of the network. Moreover, each bay of the media center can deploy to PLANET's converter family like Ethernet, Fast Ethernet twisted pair to Fiber-optic conversion, Gigabit SX to LX conversion, etc.

▶▶ KEY FEATURE

- ☐ High quality 19" Rack-Mountable Chassis
- ☐ Supports up to fifteen (15) modular media converters
- ☐ Two fans for system cooling, and LED indicators for system and fan status
- ☐ Bay power isolation, ensure each bay is electrically isolated from each other
- ☐ Support multiple converters - 10/100/1000Mbps, copper, Fiber, single/multi-mode ST/SC/MT-RJconnectors
- ☐ Reduce the effort of converter maintenance and management
- ☐ Cost-effective, easy install

>> SPECIFICATION

Product	19-inch Media Converter Chassis
Model	MC-1500
Slot	15 open slot; (27x 95 x 71 mm, WxDxH)
Dimension	438 x 200 x 103mm (W x D x H); 2.4U
Power Requirement	100 ~ 240V AC, 50 ~60Hz
Power output	+5V DC per slot, 1 A minimum
DC Output	+5VDC (+/-1%) per slot
LED indicator	3, Power, Fan A, Fan B (On: operating; Off: device or fan fail)
Environment	Temperature: 0~50 degree C (operating); -20~70 degree C (storage) Humidity: 0~90% (non-condensing)
Compliance	FCC Class A, CE-mark

>> PRODUCT POSITIONING

☐ *Fiber-optic wiring/ Media conversion center*

With up to 15-bay, this high-density media chassis can simply be a conversion center of your fiber-optic network, or a network with the demand of multiple media interfaces, in a cost-effective way.

>> ORDERING INFORMATION

- **MC-1500** 19" Media Converter Chassis with 15 slots

Distributed by:

L-com[®] CONNECTIVITY
PRODUCTS

45 Beechwood Drive
North Andover, MA 01845
www.L-com.com
E-mail: sales@L-com.com
Fax: 978-689-9484
Toll Free: 800-343-1455